

4-19-2010

Serials Label Printing with Zebra TLP Printers

Leigh Ann Duncan

Wright State University - Main Campus, leigh.duncan@wright.edu

Follow this and additional works at: https://corescholar.libraries.wright.edu/ul_pub



Part of the [Information Literacy Commons](#)

Repository Citation

Duncan, L. A. (2010). Serials Label Printing with Zebra TLP Printers. .
https://corescholar.libraries.wright.edu/ul_pub/189

This Presentation is brought to you for free and open access by the University Libraries at CORE Scholar. It has been accepted for inclusion in University Libraries' Staff Publications by an authorized administrator of CORE Scholar. For more information, please contact corescholar@www.libraries.wright.edu, library-corescholar@wright.edu.

Serials Label Printing

with Zebra TLP Printers

Leigh Duncan
Systems Librarian
Wright State University
leigh.duncan@wright.edu



Introduction

Currently, Innovative's print templates do not apply to serials labels. But that doesn't mean they can't be printed easily and efficiently!

Using a Zebra TLP 2824 printer and Rasmussen Software's Print Wizard allows for simple printing of easy-to-read labels.



■ Part One: Zebra Printer

- ◆ **Install the printer using the EPL driver**
- ◆ **Customize the label size by measuring the labels you are using**
 - **We use Bayscan Technology's Spine Labels**
- ◆ **Darken the print by selecting Printing Preferences | Document | Device Options | Head Settings**

Part Two: Print Wizard Software

- ◆ **Install Print Wizard Server Edition software**
- ◆ **Create an initialization file to configure your labels**

*Our serials
initialization file*

```
<PWML>
<PAGESIZE
  X=2.4cm
  Y=3.6cm
  length=8
  orientation=portrait
>
<FONT face="Courier New">
<B>
<BODY
  topmargin=.2cm
  leftmargin=.2cm
  rightmargin=2.5cm
  bottommargin=3.8cm
>
<LEGACY wrap=squeeze>
```

■ Part Two: Print Wizard Software

- ◆ **Modify the Print Wizard icon on your desktop**
- ◆ **Change the Properties of the icon by setting the Target to your initialization file**



```
Target = "C:\Program Files\Printwiz30\PrintWiz.exe" /listen /u  
/init=serials.init /p "Zebra TLP2824"
```

Part Three: Create the Printer

- ◆ In the character-based III system, access the **Advanced Printer Setup (A>A>L>A)**
- ◆ **Create a Workstation JetDirect printer**



Our Printer

```
01 > Menu Name      : Workstation Jetdirect
02 > Diac Map       : diac.utf8
03 > ID             : 17
04 > Printer Type   : wsjet
05 > Class          : Standard 1
06 > Type           : Network Printer
07 > Device         : LOCAL:9100
08 > User type      : Standard
09 > STTY Settings  : IXON -I XANY OPOST
10 > Confirm Print  : NO
11 > Initial String : \014
12 > Closing String : \014
13 > Maximum Columns : 80
14 > Maximum Rows   : 60
```

■ Part Four: Millennium Settings

- 1. Associate the Workstation JetDirect printer with your Millennium Serials login (via the Login Manager)**
- 2. Allow Label Printing for your Millennium Serials Login (via Manager Controlled Options)**
- 3. Make sure your checkin records have the Label Type fixed field defined to print a label**

Part Five: Label Specifications

- ◆ Access Serials Options in the character-based system (A>A>S>O>S)

2>Label
Specifications

```
Label specifications
```

```
1 > Print spine label.....YES
2 > Width of spine, in columns.....8
3 > Width of label, in columns.....1
4 > Width of gap, in columns.....3
5 > Height of label, in lines.....8
6 > Vertical space between labels on printout, in lines.....1
7 > Printer selection.....USE LOCAL PRINTER
8 > Breakmode for call number.....BREAK ON SPACE & SUBFIELD
```

Part Five: Label Specifications

- ◆ Our settings . . . these can be customized to your preferences



```
Serials checkin spine label 1
```

```
1 > Fields to print on label.....Choose to view  
2 > Format for call numbers.....LETTERS / NUMBERS & DECIMAL  
3 > Print the period preceding the Cutter number.....YES
```

■ Part Five: Label Specifications

- ◆ **Our settings . . . these can be customized to your preferences**




1 > Fields to
Print on Label

Fields to print on Serials checkin spine label 1:

1 > CALL # from CHECKIN record (period will print): Class Letters,
Numbers and Decimals all print on separate lines.

■ Part Six: Printing the Labels

- 1. Launch the Print Wizard icon on your desktop (automate this via the Windows Startup menu!)**
- 2. Log into Millennium Serials**
 - **Select your printer: File | Select Printer | Label Printer | Workstation JetDirect**
 - **Call up your checkin record**
 - **Make sure the Print Labels box is checked**
 - **Check in the title**
 - **Voila! A label will print** 

■ Example Labels

- ◆ You can specify your chosen font in Print Wizard

Courier
New

Century
Gothic

Luci da
Consol e

Consolas

**Kozuka
Gothic**